

- ✓ True Sinewave output
- ✓ High Operating efficiency
- ✓ Field Serviceable
- ✓ Automatic temperature and voltage protection
- ✓ Rugged die-cast aluminium chassis



Designed for mounting in vehicles and for remote worksite applications. Nomad Mobile inverters are suitable for both heavy duty and sensitive electronic loads. With less than 3% harmonic distortion, the Nomad Mobile delivers a true sine wave output that is identical to grid supply AC power. Designed for power tools, household equipment, electronics and more.

B505

Electrical		B505-12	B505-24	B505-48
Nominal DC input Voltage		12V DC	24V DC	48V DC
Continuous Power Rating		5000 watts	5000 watts	5000 watts
AC Voltage/Frequency		230V/50Hz	230V/50Hz	230V/50Hz
Continuous AC RMS Output		21.7 Amps	21.7 Amps	21.7 Amps
Idle Power		30 watts	40 watts	72 watts
Typical Efficiency		87%	88%	90%
AC Overload Capability	Surge (5ms)	10000 VA	10000 VA	10000 VA
	10 Seconds	6000 VA	6000 VA	6000 VA
	24 Hours	4000 VA	4000 VA	4000 VA
DC Input Voltage Range		10.6V to 15.5V	21.6V to 30V	43.2V to 63V
Low Voltage Alarm		10.5V	21V	41.8V
Low Voltage Shutdown		9.5V	19V	38V
Over voltage protection		16V	31V	65V
Low Voltage Recovery		11.8V	23.6V	47.2V
Over voltage recovery		15.7V	31.8V	63V
Protection Functions				
Low voltage LED red light, buzzer warning, automatic recovery		Short circuit within 2 seconds automatic recovery		
Over voltage LED red light, automatic recovery		Input reverse connection, Fuse burn-out		
Over-load LED red light, automatic recovery		Over temperature LED red light, buzzer warning, automatic recovery		

General

Temperature Range	-10C to +50C		
Weight	12.5kg	12kg	12kg
Dimensions (L x W x H)	54.5 x 19.9 x 14.6 cm		