

# POWER CENTER

## PC 1000



Designed to be the central appliance in your off-grid power system, the Powercenter 1000 by NOMAD provides inverter, battery charger, UPS and power clean-up functionality to your power system. Auto Voltage Regulation allows the Powercenter to run from extremely bad quality power sources, charge attached batteries and output clean standard power to its connected load. Intelligent multistage battery charging reduces generator run-time and prolongs the life of your batteries. The Powercenter is the only choice when you need a true sinewave, powerful and reliable power solution for your home, business or vehicle.



### PC 1000

Input	Voltage	140-275V
	Frequency	48-52 Hz
Output	Voltage	230V
	Frequency	50Hz
Efficiency		85-95%
Total Harmonic Distortion		0.30%
Surge rating 2 seconds:		1300w
Surge rating: 30 seconds:		1200w
UPS Type:		Line interactive
UPS Transfer time		4ms

Protection Functions	Output short-circuit , Battery high-voltage, Battery low-voltage, Battery reverse polarity
Alarm	Output Short Circuit, Low voltage, overload, 4 beeps on loss of input AC Power
Environmental Temperature	0°C~40°C
Display	Backlit LCD Displaying: AC Input Voltage and frequency, Output Voltage, Battery capacity meter, AC Loading meter, Overload indicator
Physical Size	370 x 140 x 200mm
Weight	11kg

[www.nomadpower.net](http://www.nomadpower.net)

© 2012 Nomad Power Systems. All Rights Reserved.

All trademarks owned by Nomad Systems or its affiliated companies.